


NASA TECH BRIEF



NASA Tech Briefs are issued to summarize specific innovations derived from the U.S. space program, to encourage their commercial application. Copies are available to the public at 15 cents each from the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia 22151.

MOSFET Improves Performance of Power Supply Regulator



This circuit provides a higher degree of power supply voltage regulation and temperature compensation than a conventional circuit using a zener diode as a voltage reference. This improvement is effected by using a MOSFET (Metal Oxide Semiconductor Field Effect Transistor), Q_4 , as the voltage reference in place of the zener diode. As in the case of the conventional regulator, the improved regulator utilizes a bridge circuit R_1 , R_2 , Q_4 (in place of a zener diode), and R_3 and a difference amplifier consisting of Q_1 , Q_2 , and R_4 , with R_5 allowing initial operation at power turn-on. The regulator performance is determined by the voltage difference between V_1 and V_2

produced by a change in regulator supply V_R . The difference amplifier gain and the current gain of transistor Q_3 amplify this voltage difference to determine the closed loop performance. Cross coupling of the gate of Q_4 to the base of Q_1 allows Q_4 to serve also as an additional amplifier.

Note:

Inquiries concerning this circuit may be directed to:

Technology Utilization Officer
Goddard Space Flight Center
Greenbelt, Maryland 20771
Reference: B67-10569

(continued overleaf)

Patent status:

Inquiries about obtaining rights for the commercial use of this invention may be made to NASA, Code GP, Washington, D.C. 20546.

Source: Donald C. Lokerson
(GSC-10022)